


# Denver JST-10010


- Jumpstarter powerbank with 10000mAh li-ion battery cell
- Use it to start your car, if battery runs out of power
- Works also as a normal powerbank for extra power for your phone
- input: 15V~1A
- Output: 3x5V~2A (max. 3.1A)
- 12V/16V/19V~3.5A, 12V ignition output
- 12V output port for starting car (cranking min 200A-peak 400A)
- Continuous ignition times: 15-20
- Supported vehicles: 12V gasoline under 4.0L, 12V diesel under 3.0L
- Working temperature: -20° - +60°C
- LED Light with 3 modes - Strong light, strobe light and SOS light
- Accessories included: AC adaptor, Car charger, MicroUSB cable, car clip, Notebook adaptor cable, Notebook adaptor connectors


## Safety protection clip:


*9 safety protections: short circuit, reverse polarity protection alarm, reverse charging, low-voltage, over-voltage, over-charge, over-discharge, test car battery quality, force output function, internal IC components malfunction alarm.*



 HIGHLIGHTS  
Jumpstarter powerbank, for starting car or charging smartphone, laptop etc.

 POWER  
230V~50Hz AC/DC adaptor

 BATTERY  
10000mAh lithium ion battery

 CONNECTIONS  
15V~1A from adaptor for charging the jumpstarter, 3 x 5V + 12V/16V/19V output, 12V output port for starting car (cranking min 200A-peak 400A)

## Shipping information

Unit size: 7.80(w) x 15.80(d) x 3.00(h) cm

Unit weight: 1.3

Giftbox size: 10.50(w) x 25.50(d) x 16.00(h) cm

4 pcs./export carton

6500 pcs./20' container

17000 pcs./40' HQ container

Barcode: 5706751033766