

# Denver WCM-8010

- Digital wildlife camera with 8mp CMOS
- Built-in 2.0" LCD screen
- 8mp cmos image sensor (5/8/12MP image res.)
- 2G/GSM Simcard reader - insert simcard & receive pictures via MMS and/or Email
- 3 motion sensors
- Full automatic ir filter for use in the dark - 42 leds
- Lens: F=3.09; F/NO=2.0; FOV 90°
- Pir sensing distance: 1-25 meters
- Trigger speed 0,3 second
- Standby time: up to 3 months
- MicroSD card slot for rec. - up to 32gb (card not included)
- Video resolution: 1080p,
- 720p, vga (up to 1440x1080)
- Waterproof: ip65 standard

**You can download MMSCONFIG program here:**

[MMSCONFIG](#)

You can find a guide on how to setup your camera here:


[GUIDE](#)

**Update (please pay attention to your PO/Serial number. You need to use the correct one for your camera)**




Highlights

Wildlife cam, MMS function, 8mpixel CMOS sensor, full automatic IR light with 42 LED's, IP-65 waterproof



Battery

Uses 8 x size "AA" batteries (not included)



Camera

8Mpixel CMOS sensor, 90° fixed angle



Connections

TV out, USB input, MicroSD card input, Simcard input

## Shipping information

Unit size: 9.60(w) x 8.10(d) x 13.80(h) cm

Unit weight: 0.575

Giftbox size: 16.80(w) x 12.30(d) x 11.00(h) cm

4 Pcs./export carton

10000 Pcs./20' container

24400 Pcs./40' HQ container

Barcode: 5706751039416

[Update for PO11803, 11981, 12058 & 12118, PO12176, PO12209 & PO12636](#)

1. Download and unzip the update file