# Denver MET-100 METAL DETECTOR

- Metal detector in lightweight material
- Visual indication + sound
- Simple DISC & Autotune
- Sensitivity: max dept <12cm for a US quarter
- 170mm water-resistant searching coil (can be used under shallow water)
- 1/8" headphone jack
- Low battery indication
- Adjustable stem for comfortable use - arm support carry and operate your detector comfortably
- Power supply: 6 x size "AA" batteries required (not included)
- Can find different metals & gold/silver

## To do calibration on the metal detector, please do as follows.

1. Turn on the unit and set the right knob to approximately 50% make sure not hold the plate of the metal detector close to any metal.

2. Push and hold the red button on the detector, and then adjust the "TUNE" button until it is in zero position (the yellow part).

3. Then let go of the red button, and you are ready to find metal.

After you found metal, it can be necessary to zero it again by push/hold the red button and then adjust the tune button again.

- ⚙
  Highlights
  Metaldetector, 170mm searchcoil, 12cm max search depth
- 🔋
  Battery
  Uses 6 x size "AA" batteries (not incl.)
- ◉
  Connections
  Headphone jack

## Shipping information

Unit size: 16.50(w) x 24.00(d) x 82.00(h) cm
Unit weight: 1.15
Giftbox size: 63.30(w) x 11.50(d) x 15.00(h) cm
4 Pcs./export carton
1848 Pcs./20' container
4488 Pcs./40' HQ container
Barcode: 5706751024825



**DENVER**®
denver-electronics.com